



### Driver Parameters

<b>Driver:</b>	<b>Adire Audio Shiva 12D8</b>	
Nominal Diameter	D = 12	in
Nominal Power	P = 300	Watts
Sensitivity (1W/1m)	SPL = 88.1	dB SPL
Free Air Resonance	f(s) = 27	Hz
Total Q	Q(ts) = 0.44	
Electrical Q	Q(es) = 0.46	
Mechanical Q	Q(ms) = 8.51	
Equivalent Volume	V(as) = 3.63	cu ft
Nominal Impedance	Z = 8	Ohms
DC Resistance	R(e) = 0	Ohms
Max Thermal Power	P(t) = 500	Watts
Max Linear Excursion	X(max) = 14.2	mm
Max Excursion	X(lim) = 0	mm
Voice Coil Diam.	D(vc) = 0	mm

#### Driver Notes:

NOTE: X(max) was estimated based on the nominal driver diameter.  
 NOTE: X(max) was estimated based on the nominal driver

#### System Notes:

### Box Parameters

<b>System Type:</b>	<b>4th Order Vented Box</b>	
Box Volume	V(B) = 5	cu ft
Closed Box Q	Q(tc) = 0.5781	
Box Frequency	F(B) = 25	Hz
Min Rec Vent Area	S(vMin) = 20.2	sq in
Vent Surface Area	S(v) = 28.27	sq in
Vent Length	L(v) = 20.1	in
Compliance Ratio	alpha = 0.726	
Box Loss Q	Q(B) = 7	

### System Parameters

No. of Drivers	N = 1	
Isobarik Factor	I = 1	(1=normal, 2=iso)
Input Power	P(in) = 300	Watts
SPL Distance	D = 1	m

<h2>Joe's Subs</h2>	
2261 Kristin Drive Troy, MI, 48084 USA	
248-459-9075	
System Name:  <b>4th Order Vented Box</b>	
Designer:	Joe Gerhardstein
Title:	Senior Designer
Rev Date:	Rev: